

Pre-Wired Victron Boards

Mains Charger

Capable of mains charging at up to 120A.

Solar Charging

Capable of charging up to 50A. Recommended solar capacity 600 – 800W.

DC-DC Charging

30A charge rate and compatible with smart alternators and configurable via Bluetooth.

Combined Charging

The combined charge rate is 200A. The charge rate can be limited through the Cerbo GX.

240V Inverter

3000VA / 16A transfer switch with 5500W surge capacity





Warning

To maximise the longevity and safety of your new Victron Pre-Wired Board, please ensure you follow stay within the specified parameters and connect to the appropriate terminals referring to the wiring diagram. Failure to do so could result in shortened lifespan and void your warranty.

This equipment contains 240V equipment – **serious injury and/or death** can occur when working with these voltages. Only competent/licenced persons must connect to the 240V supply.

Risk of fire/explosion – do not short circuit the equipment or exceed voltages. Always check polarity before powering equipment on. Do not expose to the weather or allow water ingress. Keep out of excess dust and do not exceed temperature ratings. Always select appropriate fuse sizes and ensure suitably tight connections.

EXOTRONIC Electronics for the Great Outdoors

Specifications

11.2 – 17V
250Ah
250A Continuous Current
3000VA / 2400W
2200W
5500W
93%
20W
187 – 265VAC 45- 65Hz
120A
50A
30A
200A
87%
14.2V - Adjustable
13.5V - Adjustable
11.5V for 30s - Adjustable
100V
0-1200W
(600-800W recommended)
60A
98%
5C - 45C
(0C - 65C storage)
780 x 530 x 170mm
1200 x 355 x 170mm
33kg

More details available on individual component data sheets if needed.

