

1 **ADD OIL: 1.6 Litre SAE 10W-30**
Place unit on a flat surface. Remove the oil dipstick. With the funnel supplied add 1.6 Litre SAE 10W-30 oil. Replace dipstick and tighten.

2 **ADD FUEL:**
Fill the fuel tank with clean unleaded petrol. Note that the fuel tank capacity is 45 Litres.

3 **STARTING THE GENERATOR:**
1) Ensure that the generator is placed in a well ventilated area.
2) Ensure that there are no electrical appliances plugged into the generator.

Turn the Fuel Switch to the **"ON"** position.

5 **Battery connection**
Fasten the black negative wire on the negative terminal of the battery

6a **PUSH - BUTTON START:**

1) Press the Battery Switch (Red Switch) to the **"ON"** position.



2) Press & hold the Start Button for 4 seconds and wait for the generator to start.
3) Once the generator is running smoothly you can then connect the appliances.

CAUTION:

- 1) BE CAREFUL TO NOT OVERLOAD the generator.
- 2) DO NOT PLUG THE GENERATOR DIRECTLY INTO A WALL SOCKET.

6b **Remote Start:**



- 1) Press the Battery Switch (Red Switch) to the **"ON"** position.
- 2) Press the **"Start"** Button on the Remote.

7 **TO STOP:**

- 1) Turn the Fuel Switch to the **"OFF"** position.
- 2) Turn **"OFF"** the Switch (Red Switch).
- 3) Press the Push - Button Start.
- 4) Hold down the Remote **"STOP"** button for 3 seconds.
- 5) Disconnect the appliances from the generator.



NOTE CAUTION!

If the BATTERY SWITCH (RED SWITCH) is left in the **"ON"** when the generator is turned off, the Battery **WILL** run flat!

REVIEW AND UNDERSTAND YOUR OWNERS MANUAL AND ALL WARNINGS BEFORE RUNNING YOUR GENERATOR

WARNING

- Read and understand the Operator's Manual thoroughly before operating the generator to avoid any serious injury or even death.
- Fire hazard. Do not add fuel while generator is on.
- Generator is a potential source of electric shock. Do not expose to moisture, rain or snow. Do not operate with wet hands or feet.

- Exhaust fumes contains poisonous carbon monoxide gas that can cause unconsciousness or DEATH. Operate in well ventilated, outdoor areas away from open windows or doors.
- Prior to connecting any appliance to the generator, check the rating label of the appliance. Refer to manual for details.
- Do not expose to rain or use in damp locations.

DANGER

- Using a generator indoors CAN KILL YOU IN MINUTES. Exhaust fumes contain carbon monoxide. This is a highly poisonous gas that can not be seen or smelt.
- NEVER use inside home or garage, EVEN IF doors and windows are open.
- Only use OUTSIDE and far away from windows, doors and vents.

