


HOME / SOLAR OFF THE GRID / WORKSITE



2
YEAR
WARRANTY

MAXWATT
POWER WHEN YOU NEED IT

Why Choose MaxWatt?

No matter what you are preparing for, our wide range of MaxWatt products will deliver beyond expectation. Every detail of our products has been well-thought-out and expertly designed using only the highest quality components. Our commercial and residential generators can handle large power generation requirements making them ideal for worksites, free camping, and farming applications. With a two-year warranty, the Maxwatt products are designed to provide peace of mind and power when you need it most!

MX13000AS

Barcode: 9356905000173

Worksite GENERATORS

13.5 kVA / 11000W Petrol Generator with 2 Wire Auto Start



- 11000 Starting Watts /10000 Running Watts.
- 688 cc V Twin Petrol Engine.
- 2 x 15 Amp IP66 Weatherproof Outlets.
- 1 x 32 Amp IP66 Weather Proof Outlet For Maximum Power From One Outlet.
- Digital Automatic Voltage Regulator - For Stable Output.
- Digital Display indicating Voltage, Frequency, Total Running Hours.
- Massive 45 L Fuel Tank.
- 10 Hours Run Time At 50% Load Or 6 Hours At 100% Load.
- 36 AH Lead Acid Battery.
- Push Button Start and Recoil Starting Method.

Technical Information

Voltage (V)	240V
Amperage (A)	43.8A
Displacement (cc)	688cc
Fuel Tank Capacity (L)	45L
Rated Power (Watts)	10kW
Max. Power (Watts)	11kW

Noise Level (dB's) at 7m @ 75% Load	96
Weight (Net)	167kg
Ignition	Electric
Rated Frequency	50Hz
Cont. Running Time @50% Load	10 hrs
Cont. Running Time @100% Load	6 hrs

Generator Dimensions
Length 730mm | Width 600mm | Height 780mm | Weight 167kg

Box Dimensions
Length 785mm | Width 655mm | Height 950mm | Weight 192kg