

6.5KW CROMTECH AVR PETROL GENERATOR



SPECIFICATIONS

MODEL NUMBER

Max. Watts (w) Cont. Output (w) Starting System

Phase **Fuel Type**

15amp outlet s/phase

Engine Brand Voltage (V) Fuel Tank (L)

Noise Level (dB @ 7m)

Weight (kg)

Dimensions (LxWxH)

Package (LxWxH)

Manufacturers Warranty

Barcode

TG6500VE

6500w 6000w

Electric start

Single Petrol

2x 15Amp

420cc Cromtech

240v - 50hz

25L 74db 87kg 715 x 545 x

605mm 715 x 545 x 605mm 1 Years

9336493005637

Designed for general use, this 6500watt AVR electric start generator is perfect for onsite power for tradies. It is also suitable for residential, farms and fetes. The model comes with wheels and fold-out handles to make it easily portable around IDEAL FOR the site.





STANDARD FEATURES

- 2x Outlets (single phase 15 Amp)
- RCD and overload protection switches
- Electric start and recoil start
- Fold-out handles
- Steel frame with large wheels
- Petrol powered
- 4-Stroke, air cooled, OHV Cromtech engine
- Hours operation, Hz, Voltage meter
- Battery charging (12V-8.3AMP)
- Low oil alarm, overload alarm, output indicator
- Large 25L fuel tank
- 1 Year Cromtech warranty

- General purpose use
- ► Tradies and residential
- Farm and rural
- Fetes and markets

INDUSTRY

- Construction
- Building
- Trade
- Domestic





