

Honda Powered Remote Start Generator

Perfect for backing up your solar power, this 8KVA Honda powered generator comes standard with a remote start and a 30L long range fuel tank.

Features of the upgraded EP8000HSRE-R/S

Engine Reliable electric key start Honda GX390 engine

NSM Alternator With less than 6% harmonic distortion to run electronic equipment and tools

Remote Start 2 wire remote start , to allow you to start your generator without going out to it

Newly Designed Frame Extremely strong steel frame with protective top cover

Centre Point Lift To allow for easy lifting

Long Range Fuel Tank Extra large 30L base mounted fuel tank

8kVA Honda with Remote Start

Centre Point Lift Model: EP8000HSRE-R/S


Newly Designed Frame

Lighter!

Honda Electric Key Start Engine



Remote Start



30 L Fuel Tank









The Perfect Back up Generator

The controller on the remote start kit will start the generator from the closure of a remote contact. Which really makes this unit the perfect back-up generator for unreliable solar power.







EP8000 H		ISRE-R/S Specifications
GENERATOR	Rated Voltage	230V
	Frequency	50Hz
	Rated Output	8 kVA
	Alternator Rating	9.5 kVA
ENGINE	Engine Type	Honda GX390
	Starting System	Recoil / Electric - Remote Start
GENERAL	Size - LxWxH (mm)	800 x 545 x 575
	Dry Weight	120kg
	Fuel Tank Capacity	30L
	Noise Level (7m)	74 dbA
	Brushless Alternator	✓
	Auto Decompressor	✓
FEATURES	Centre Point Lift	✓
	Extendable Handles	Optional raised wheel kit
	Rubber Feet	✓
	Low Oil Level Warning	✓
	AC Plug	✓
	Transportation Kit	Optional raised wheel kit

Optional Extra Solar Panel Kit Maintains the charge in your battery when your generator is not in use Raised Wheel Kit Includes extendable handles and 2 wheels.

Remote Start Kit