

6800W Petrol Powerlite Generator - PH080E24000RC Powered by Honda

Powerlite's remote start/stop generator is perfect for roofers, brickies or anybody that needs a generator ready at the touch of a button. Takes away the hassle of having to climb down off the roof to start the generator.



Infrared remote Control
Up to 100m range
(Line of sight)

Model - PH080E24000RC

Product Description

6,800W Petrol Powerlite Generator, powered by Honda, electric & recoil start with RCD, 2 weatherproof socket outlets, wheels & handle frame & battery. WorkCover compliant, essential for construction sites. Ideally used for portable electric tools, 140 Amp welder (on light duty), shearing plant, air compressor (with up to 2.2kW electric motor), heaters, lights, appliances and excellent motor starting and welder performance, provided that the total power consumption at any one time is less than 6,800W.

Specifications

Industry rating	8 kVA
Real power	6800 watts
Engine	13 hp Honda
Starting	Electric
Phase	Single
Fuel	Petrol
Frame	Roll
Tank litres	6.5
Fuel litres per hour	2.5
Weight	73 kg
Outlets	1x10A & 1x15A
Dimensions (LxWxH mm)	860x500x540
Infrared remote control	Fitted

Options	PH080E	PH080E13000	PH080E14000	PH080E20000	PH080E23000	PH080E24000
Recoil	✓	✓	✓	✓	✓	✓
Electric (Battery Optional)	✓	✓	✓	✓	✓	✓
25mm Scoop Frame	✓	✓	✓	✗	✗	✗
RCD Protection	✗	✓	✓	✗	✓	✓
2 x IP66 Outlets	✗	✗	✓	✗	✗	✓
Wheel and Handle Roll Frame	✗	✗	✗	✓	✓	✓

Powerlite
POWER • LIGHTING • TRAFFIC

P 02 9912 5000 F 02 9912 5001 E sales@powerlite.com.au W powerlite.com.au
2 Binney Road, Kings Park NSW 2148

